

[Get a Quote](#)

Overview

1-ch input and 2-ch output PoE relay function

Supports EXTEND mode of PSE (Power Sourcing Equipment) output interface: the transmission distance of a single-stage network can be extended to 250 meters when EXTEND mode is enabled

Uses standard Cat. 5e twisted pair. For 10/100 Mbps mode, the repeater supports 4-stage cascade and the max. transmission distance reaches 500 meters (terminal power consumption < 5W). For EXTEND mode, the max. transmission distance reaches 400 meters (terminal power consumption < 5W)

Specification

DS-1H34-0102P Specification	
General	
EFT	Network port: ± 2 KV
Dimensions(W*H*D)	71.6 \times 26.1 \times 95.5 mm (2.8 \times 1.0 \times 3.8 inch)
Working Temperature	-30 $^{\circ}$ C to +70 $^{\circ}$ C (-22 $^{\circ}$ F to +158 $^{\circ}$ F)
Working Humidity	10% to 90%
Weight	0.3 Kg (0.7 lb)
MTBF	100000 hours
ESD	Contact discharge: ± 7 KV Air discharge: ± 9 KV
Surge	Power port: Line-to-ground: ± 2 KV; Line-to-line: 1 KV Network port: Line-to-ground: ± 4 KV
Consumption	< 2W
Dimensions (W*H*D)	71.6 \times 26.1 \times 95.5 mm (2.8 \times 1.0 \times 3.8 inch)
External Interface	
Audio Input/Output	1-ch 10/100BaseT(X) and IEEE 802.3at standard of PD connection.2-ch 10/100BaseT(X) and IEEE 802.3af standard of PSE outputs.

Want to Buy

[Order Now](#)

[Get a Quote](#)

Why Router-switch.com

As a leading network hardware supplier, Router-switch.com focuses on original new ICT equipment of [Cisco](#), [Huawei](#), [HPE](#), [Dell](#), [Hikvision](#), [Juniper](#), [Fortinet](#), etc.





200+

Countries we Sold



18,000+

Customers Trusted



\$20,000,000

Inventory Available



50%-98%

Off Global List Price



100%

Safe Online Shopping

Contact Us

- Tel: +1-626-655-0998 (USA) +852-3050-1066 / +852-3174-6166
- Fax: +852-3050-1066 (Hong Kong)
- Email: sales@router-switch.com